



EXCLUSIVE KIT WITH THE WORLD'S FAVORITE CHARGER

The MXS 5.0 POWER KIT includes the popular MXS 5.0 battery charger and selected accessories for optimal battery care. Plus a CTEK powerbank ensures your electronic devices stay powered up wherever you go. Designed for performance, convenience and unbeatable value, this kit is a must-have for every vehicle owner.

EXCLUSIVE KIT - PREMIUM VALUE, LIMITED STOCK

The MXS 5.0 battery charger is one of the world's most advanced and trusted 12V chargers, designed for fast, safe and fully automatic charging and maintenance. Featuring temperature compensation, reconditioning mode and support for AGM batteries, it ensures optimal performance and extended battery life for cars, motorcycles and more. The included INDICATOR EYELET M8 allows for easy battery monitoring, while the CONNECT CLAMP provides a quick and secure connection. And as a bonus, this kit also includes a 5000 mAh CTEK powerbank, so you can keep your electronic devices charged wherever you go

- Limited edition kit with the world's favorite charger
- 5000 mAh Powerbank included
- Monitor battery health with INDICATOR EYELET M8
- Quick and secure connection with CONNECT CLAMP
- Safe and fully automatic charging with MXS 5.0
- Charge lead-acid batteries up to 110Ah
- Safe spark free operation
- Reverse polarity protected
- Short circuit proof
- Fully automatic 'connect and forget' 8 step 12V charging
- Smaller battery, normal battery, AGM and Recond programs
- Built in automatic temperature compensation

MXS 5.0 POWER KIT NA



TECHNICAL DATA

INPUT	110-120 VAC, 50-60 Hz
OUTPUT	14.4/14.7/15.8 V, 4.3 A
CHARGER TYPE	8 step, fully automatic charging cycle
BATTERY TYPES	12 V: WET, MF, Ca/Ca, AGM, EFB, GEL
BATTERY CAPACITY	1.2-110 Ah, maintenance charging up to 160 Ah
START VOLTAGE	2.0 V
BACK CURRENT DRAIN*	corresponding to less than 1Ah/month
RIPPLE**	Less than 4 %
POWER SOURCE	120 V -> 12 V
BATTERY VOLTAGE	12 V
AMBIENT OPERATING TEMPERATURE	-4 °F to +122 °F
TEMPERATURE COMPENSATION	Built-in compensation of charging voltage based on ambient temperature.
BATTERY CHEMISTRY	Lead acid
DEGREE OF PROTECTION	IP65
WARRANTY	5 years MXS 5.0, 2 years accessories

*) Back current drain is the current that drains the battery if the charger is not connected to the power outlet. CTEK chargers have a very low back current.

**) The quality of the charging voltage and charging current is very important. A high current ripple heats up the battery which has an aging effect on the positive electrode. High voltage ripple could harm other equipment that is connected to the battery. CTEK battery chargers produce very clean voltage and current with low ripple.

GUARANTEED QUALITY WITH CTEK

CTEK customer support is available to answer any questions related to charging and CTEK chargers. Safety, simplicity and flexibility characterizes all products and solutions developed and sold by CTEK. CTEK supplies chargers to more than 70 countries throughout the world. CTEK is also a reliable OEM supplier to many of the world's most prestigious car and motorcycle manufacturers.

For more information visit
WWW.CTEK.COM